

Honeywell RT10A - tablet - Android 9.0 (Pie) - 32 GB - 10.1" - 4G



06-07-2024

SKU	RT10A-L1N-17C12S1E
Produktbeskrivelse:	Honeywell RT10A - tablet - Android 9.0 (Pie) - 32 GB - 10.1" - 4G
Produkttype:	Tablet - grov
Operativsystem:	Android 9.0 (Pie)
Billedskærm:	10.1" - 1920 x 1200
Processor:	Qualcomm Snapdragon (8 kerner) - 64-bit
Processors clockhastighed:	2.2 GHz
Lagring:	32 GB

Generelt

Produkttype:	Tablet - grov	Min. d
Operativsystem:	Android 9.0 (Pie)	Maks.

Billedskærm

Type:	10.1"	Min. l
Opløsning:	1920 x 1200	Maks. Opbev
Funktioner:	Synlig udendørs, optisk binding	

Processor

Processor:	Qualcomm Snapdragon	Prod
Processors clockhastighed:	2.2 GHz	Service
Antal kerner:	8 kerner	Mål
64-bit Computing:	Ja	Bredd

Hukommelse

Lagring:	32 GB	Dybde
RAM:	4 GB	Højde:
Understøttede flashhukommelseskort:	microSD, microSDHC, microSDXC	Vægt:
Max understøttede kapacitet:	512 GB	Dive
Kompatibilitet:	microSDIO	Senso

Kommunikationer

Mobilteknologi:	4G	
Mobilprotokoller:	GSM, GPRS, UMTS, EDGE, HSPA+, LTE Advanced, FDD LTE, TDD LTE	

Kommunikationer

Bånd:	GSM/GPRS/EDGE 850/900/1800/1900 / HSPA+ B1/B19/B2/B4/B5/B6/B8/B9 / LTE B1/B12/B13/B17/B19/B2/B20/B25/B26/B28/B29/B3/B38/B39/B4/B40/B41/B5/B7/B8	
Maks. overførselshastighed:	400 Mbps	
Trådløs tilslutning:	802.11a/b/g/n/ac, NFC, Bluetooth 5.0 LE	
Sikkerhedsprotokoller og egenskaber:	WEP, WPA, WPA2, WPA2-Enterprise, OPEN, WPA-Enterprise	
Bluetooth-profiler:	Hands-Free Profile (HFP), Object Push Profile (OPP), Serial Port Profile (SPP), Advanced Audio Distribution Profile (A2DP), Audio/Video Remote Control Profile (AVRCP), Phonebook Access Profile (PBAP), Generic Attribute Profile (GATT)	

Bagkamera

Sensoropløsning:	13 Megapixel
Lyskilde:	Flash

Frontkamera

Sensoropløsning:	8 Megapixel
------------------	-------------

Navigationssystem

Modtager:	GPS/GLONASS/Galileo/BeiDou
-----------	----------------------------

Multimedie

Audio:	Mikrofon, stereohøjttalere
--------	----------------------------

Dive

Egens

Sikker

Overe

Battu

Kapac

Eksp

Udvid
Holder

Interfa

Prog

Præ-l

Stre

Stregh

Scan e

Indg

Type:

